

## Solutions to Lab 3

One possible solution is shown below.

```
/*
 APSC 380 Lab 3 - Display student number in binary on LEDs.
 Ed Casas, November 1 1997
 */

#include <8051.h>

char digit [10] = { 0xf, 1, 2, 3, 4, 5, 6, 7, 8, 0xf } ;

main ()
{
    int i ;

    /* initialize index */
    i = 0 ;

    /* show digits */

    while ( i < 10 ) {

        /* display digit */
        P1 = digit [ i ] * 16 ;

        /* wait for button to be pressed */
        while ( ( P3 & 0x20 ) != 0x20 ) ;

        /* wait for button up */
        while ( ( P3 & 0x20 ) == 0x20 ) ;

        /* increment index to select next digit */
        i = i + 1 ;
    }

    /* wait forever */
    while ( 1 ) {
    }
}
```